



## Glavno

Device short name	OF
Product or component type	Auxiliary contact
Range compatibility	Compact NS1600b...3200 Compact NS630b...1600
Offer type	C4 C5
Signal contacts composition	1 NO/NC

## Komplementarno

Auxiliary contacts type	Low level
Mounting mode	Clip-on
[Ith] conventional free air thermal current	5 A
[Ie] rated operational current	Utilisation category DC-12: 0.3 A network: DC at 250 V Utilisation category DC-12: 0.6 A network: DC at 110 V Utilisation category DC-12: 2.5 A network: DC at 48 V Utilisation category DC-14: 0.03 A network: DC at 250 V Utilisation category DC-14: 0.05 A network: DC at 110 V Utilisation category DC-14: 0.2 A network: DC at 48 V Utilisation category DC-14: 1 A network: DC at 24 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 110 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 220/240 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 250 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 380/440 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 48 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 480 V Utilisation category AC-15: 0.1 A network: AC 50/60 Hz at 480 V Utilisation category AC-15: 1.5 A network: AC 50/60 Hz at 380/440 V Utilisation category AC-15: 2 A network: AC 50/60 Hz at 220/240 V Utilisation category AC-15: 2.5 A network: AC 50/60 Hz at 110 V Utilisation category AC-15: 3 A network: AC 50/60 Hz at 24 V Utilisation category AC-15: 3 A network: AC 50/60 Hz at 48 V Utilisation category DC-12: 5 A network: DC at 24 V Utilisation category AC-12: 5 A network: AC 50/60 Hz at 24 V
Minimum load	1 mA at 4 V DC

## Okolina

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.  
Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.  
Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.  
Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.