



Glavno

| | |
|---------------------------|---|
| Range | ARGUS |
| Product or component type | Movement detector |
| Load type | Incandescent lamp: 1000 W - 230 V AC Low voltage halogen lamp with wire-wound transformer: 500 VA Low voltage halogen lamp with electronic transformer: 250 VA Fluorescent tube: 200 VA - 230 V AC Compact fluorescent lamp: 3 x 23 W - 230 V AC Capacitive: : 6 A, 21 μF - 230 V AC Capacitive: : 10 A, 14 μF - 230 V AC Halogen lamp: 900 W - 230 V AC |
| Colour tint | White |
| Type of packing | Carton |

Komplementarno

| | |
|--------------------------------|---|
| [Ue] rated operational voltage | 220...240 V |
| Network frequency | 50 Hz |
| [Ue] rated operational voltage | 220...240 V |
| Output current | 10 A |
| Type of setting | Light sensitivity adjustable Time adjustment |
| Time delay | 3 s...30 min |
| Light intensity adjustment | 5...2000 lux |
| Horizontal detection angle | 0...120 ° |
| Detection face | Frontal 12 m |
| Material | PC (polycarbonate) with matt surface |
| Device mounting | Surface |
| Mounting height | 2.5 m |

Okolina

| | |
|---------------------------------------|--------------|
| IP degree of protection | IP55 |
| ambient air temperature for operation | -15...40 °C |
| environmental health and issues | Halogen free |

Offer Sustainability

| | |
|---|---|
| Green Premium product | Green Premium product |
| Compliant - since 0903 - Schneider Electric declaration of conformity | Compliant - since 0903 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Available | Available |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.