

GV7AB11

TeSys GV7 – pomoćni kontakt – 1 NO +
niskonaponski



Glavno

Range	TeSys
Product or component type	Auxiliary contact block
Product compatibility	GV3ME80 GV7R GV7RE GV7RS
Device short name	GV7AB
Range compatibility	TeSys TeSys GV7

Komplementarno

Auxiliary contacts operation	Low level Standard
Pole contact composition	1 C/O
[Ui] rated insulation voltage	690 V - for control circuit - conforming to IEC 60947-1
[Ue] rated operational voltage	110 V AC for control circuit 110 V DC for control circuit 230...240 V AC for control circuit 24 V AC for control circuit 24 V DC for control circuit 250 V DC for control circuit 380...415 V AC for control circuit 440 V AC for control circuit 48 V AC for control circuit 48 V DC for control circuit 690 V AC for control circuit
Mechanical durability	50000 cycles
Minimum switching current	5 mA for control circuit
Connections - terminals	Control circuit: screw clamps terminals 1 cable 1.5 mm ² - cable stiffness: flexible - with cable end Control circuit: screw clamps terminals 1 cable 1.5 mm ² - cable stiffness: flexible - without cable end Control circuit : screw clamps terminals 1 - cable stiffness: solid
Product weight	0.015 kg

Okolina

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0744 - Schneider Electric declaration of conformity	Compliant - since 0744 - Schneider Electric declaration of conformity

Contractual warranty

Warranty period	18 months
-----------------	-----------

GV7 AE11, GV7 AB11

Add-on auxiliary contacts according to their location

Location 1 C/O contact	Location 2 Trip indication	Location 3 Electrical fault indication	Location 4 C/O contact
---------------------------	----------------------------	---	------------------------

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.
 Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.
 Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.
 Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

11 14
12

91 94
92

81 84
82

21 24
22