

## LA1DX02

TeSys D - pomoćni kontakti blok - 2 NC - priključak vijčanim stezaljkama



### Glavno

Range of product	TeSys D TeSys D control relay
Range	TeSys
Device short name	LA1
Product or component type	Auxiliary contact block
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 NC (sealed)
Connections - terminals	Screw clamp terminals 1 cable 1...2.5 mm <sup>2</sup> - cable stiffness: flexible - with cable end Screw clamp terminals 1 cable 1...2.5 mm <sup>2</sup> - cable stiffness: flexible - without cable end Screw clamp terminals 2 cable 1...2.5 mm <sup>2</sup> - cable stiffness: flexible - with cable end Screw clamp terminals 2 cable 1...2.5 mm <sup>2</sup> - cable stiffness: flexible - without cable end Screw clamp terminals 1 cable 1...2.5 mm <sup>2</sup> - cable stiffness: solid Screw clamp terminals 2 cable 1...2.5 mm <sup>2</sup> - cable stiffness: solid

### Komplementarno

Mounting location	Front
[Ui] rated insulation voltage	250 V - conforming to IEC 60947-5-1
[Ue] rated operational voltage	<= 50 V
Mechanical durability	5 Mcycles
Minimum switching current	0.3 mA
Minimum switching voltage	3 V
Insulation resistance	> 10 MOhm
Product weight	0.04 kg

### Okolina

environmental characteristic	Harsh environment
standards	IEC 60947-5-1 VDE 0660
product certifications	CSA UL
IP degree of protection	IP2x conforming to VDE 0106
protective treatment	TH conforming to IEC 60068
ambient air temperature for operation	-25...70 °C
ambient air temperature for storage	-25...70 °C

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0944 - Schneider Electric declaration of conformity	Compliant - since 0944 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.