



### Glavno

Product or component type	Logic I/O card
Range compatibility	Altivar 61 Altivar 71 Altivar Lift Altivar 61Q Altivar 71Q
Supply	Internal supply for reference potentiometer, 10.5 V DC (10...11 V) , <= 0.01 A, impedance: 1...10 kOhm for overload and short-circuit protection Internal supply, 24 V DC (21...27 V) , <= 0.2 A for overload and short-circuit protection
Discrete output number	5
Discrete output type	(R3A, R3B, R3C) configurable relay logic (LO1, LO2) assignable logic, sampling time: 1.5...2.5 ms, compatible with level 1 PLC
Discrete output logic	(LO1, LO2) negative (LO1, LO2) positive
Discrete input number	4
Discrete input type	(LI7...LI10) programmable, , compatible with level 1 PLC, impedance: 3.5 kOhm, sampling time: 1.5...2.5 ms
Discrete input logic	(LI7...LI10) negative state 0 >= 16 V state 1 <= 10 V (LI7...LI10) positive state 0 <= 5 V state 1 >= 11 V

### Komplementarno

Electrical durability	100000 cycles for configurable relay logic output(s)
Discrete output voltage	24 V DC (voltage limits: 12...30 V) assignable logic
Maximum output current	0.2 A, assignable logic
Minimum switching current	Configurable relay logic 3 mA for 24 V DC
Maximum switching current	Configurable relay logic 2 A at 250 V AC on inductive load, cos phi = 0.4 and L/R = 7 ms Configurable relay logic 2 A at 30 V DC on inductive load, cos phi = 0.4 and L/R = 7 ms Configurable relay logic 5 A at 250 V AC on resistive load, cos phi = 1 Configurable relay logic 5 A at 30 V DC on resistive load, cos phi = 1
PTC probe input	TH1+, TH1- trip resistance, impedance: 3 kOhm TH1+, TH1- reset resistance, impedance: 1.8 Ohm TH1+, TH1- short circuit protection, impedance: < 0.05 Ohm TH1+, TH1- for 6 PTC probe, impedance: <= 1.5 Ohm
Discrete input voltage	24 V DC (voltage limits: <= 30 V) for programmable
Electrical connection	Terminal, 1.5 mm <sup>2</sup> / AWG 16, 0.25 N.m
Product weight	0.3 kg

### Okolina

### Contractual warranty

Warranty period	18 months
-----------------	-----------

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.