

170NEF11021

Modicon Momentum - komunikacijski adapter
Modbus Plus



Glavno

Range of product	Modicon Momentum automation platform
Product or component type	Modbus Plus communication adaptor
Bus manager PLC	Compact 984 Quantum
Structure type	Industrial
Communication port protocol	Modbus Plus
Method of access	Peer to peer Token bus
Transmission rate	1 Mbit/s
Transmission support medium	Twisted pair

Komplementarno

Topology	Multidrop, device connecting by extension or tap off cable
Number of devices per segment	0...31 per segment 0...63 all segment
Cable distance between devices	5000 m with repeater
Data format	984
Fail state	Fallback to zero Forcing to state zero Full scale value Maintain value
Supply	From I/O base
Marking	CE
Local signalling	1 LED green module powered up or communicating (MB + ACT) 1 LED red communication error network A (ERR A) 1 LED red communication error network B (ERR B)
Electrical connection	1 connector SUB-D 9 for connecting Modbus Plus network 1 connector SUB-D 9 for redundant Modbus Plus network

Okolina

product certifications	CSA UL
protective treatment	TC
resistance to electrostatic discharge	4 kV contact IEC 801-2 8 kV on air IEC 801-2
resistance to electromagnetic fields	10 V/m 80...1000 MHz IEC 801-3
ambient air temperature for operation	0...60 °C
ambient air temperature for storage	-40...85 °C
relative humidity	95 % without condensation
operating altitude	<= 5000 m

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1101 - Schneider Electric declaration of conformity	Compliant - since 1101 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold

Contractual warranty

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poipunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

