



Glavno

| | |
|---------------------------|------------------------------|
| Range | Acti 9 |
| Product name | Acti 9 iPB |
| Product or component type | Push-button |
| Device short name | IPB |
| Standards | IEC 60669-1 IEC 60947-5-1 |

Komplementarno

| | |
|--|--|
| Contacts type and composition | 1 NO |
| [Ie] rated operational current | 20 A |
| [Ue] rated operational voltage | 250 V AC |
| Control type | 1 push-button grey |
| Mounting mode | Fixed |
| Mounting support | 35 mm symmetrical DIN rail |
| Comb busbar and distribution block compatibility | Upside: Libro Upside: ProDis Upside: Clario |
| 9 mm pitches | 2 |
| Height | 82 mm |
| Width | 18 mm |
| Depth | 71 mm |
| Colour | White |
| Electrical durability | AC-22: 30000 cycles AC 50/60 Hz |
| Connections - terminals | Staggered tunnel terminal 1 cable(s) 0.5 mm ² rigid Staggered tunnel terminal 1 cable(s) 0.5 mm ² flexible Staggered tunnel terminal 1 cable(s) 0.5 mm ² flexible with ferrule Staggered tunnel terminal 2 cable(s) 2.5 mm ² rigid Staggered tunnel terminal 2 cable(s) 2.5 mm ² flexible Staggered tunnel terminal 2 cable(s) 2.5 mm ² flexible with ferrule |
| Wire stripping length | 9 mm |
| Tightening torque | 1 N.m |

Okolina

| | |
|---------------------------------------|----------------|
| tropicalisation | 2 |
| relative humidity | 95 % (55 °C) |
| ambient air temperature for operation | -35...70 °C |
| ambient air temperature for storage | -40...80 °C |

Offer Sustainability

| | |
|---|---|
| Not Green Premium product | Not Green Premium product |
| Compliant - since 0627 - Schneider Electric declaration of conformity | Compliant - since 0627 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.