



## Glavno

|                           |   |
|---------------------------|---|
| Range of product          | EasyPact                                |
| Range                     | EasyPact                                |
| Device short name         | Busbar                                  |
| Product or component type | Busbar                                  |
| Device application        | Connection                              |
| Range compatibility       | EasyPact - EasyPact EZB circuit breaker |
| [In] rated current        | 400 A                                   |
| Number of ways            | 4                                       |

## Komplementarno

|  |                                   |
|--|-----------------------------------|
| [Ui] rated insulation voltage            | 690 V AC 50/60 Hz                 |
| [Ue] rated operational voltage           | 550 V AC 50/60 Hz                 |
| Number of devices                        | 12 ( 1P )<br>4 ( 3P )<br>6 ( 2P ) |
| Busbar extension                         | 2 or 4 ways                       |
| [Icw] rated short-time withstand current | 40 kA ( 1 s )                     |
| Height                                   | 290 mm                            |
| Width                                    | 416 mm                            |
| Depth                                    | 107 mm                            |

## Okolina

|           |           |
|-----------|-----------|
| standards | IEC 60439 |
|-----------|-----------|

## Contractual warranty

|                 |           |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.