

MTN5510-1219

ARGUS detektor prisutnosti s IR - relej 2 ganga, polarno bijeli



Glavno

| | |
|---------------------------|--|
| Range | ARGUS |
| Product or component type | Presence detector |
| Load type | Halogen lamp: 2000 W - 230 V AC Motor: : 1000 VA - 230 V AC Capacitive: : 10 A, 140 µF - 230 V AC Incandescent lamp : 2200 W - 230 V AC Low voltage halogen lamp with wire-wound transformer : : 500 VA - 230 V AC Low voltage halogen lamp with electronic transformer : : 1050 VA - 230 V AC Energy saving lamp : : 100 VA |
| Colour tint | Polar white |
| Colour code | RAL 9010 |
| Type of packing | Carton |

Komplementarno

| | |
|--------------------------------|---|
| [Ue] rated operational voltage | 220/230 V |
| Network frequency | 50/60 Hz |
| Input compatibility | Push-buttons and electronic insert |
| [Ue] rated operational voltage | 220/230 V |
| Input function | 2 x external triggering over PL |
| Output current | 10 A 4 A |
| Number of channels | 2 |
| Type of setting | Light sensitivity adjustable Time adjustment |
| Control type | Remote control |
| Function available | Master function |
| Time delay | 10 s...30 min 5...120 min |
| Light intensity adjustment | 10...1000 lux |
| Horizontal detection angle | 0...360 ° |
| Detection face | Radius 7 m |
| Material | PC (polycarbonate) with brilliant surface |
| Device mounting | Ceiling |
| Mounting height | 2.5 m |

Okolina

| | |
|---------------------------------------|--------------|
| IP degree of protection | IP20 |
| ambient air temperature for operation | 0...25 °C |
| environmental health and issues | Halogen free |

Offer Sustainability

| | |
|---|---|
| Not Green Premium product | Not Green Premium product |
| Compliant - since 1101 - Schneider Electric declaration of conformity | Compliant - since 1101 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.