



### Glavno

Range of product	Modicon M241
Product or component type	Analogue input cartridge
Product specific application	Hoisting applications
Product compatibility	Modicon M241C
Analogue input number	2

### Komplementarno

Analogue input type	Current, input range: 4...20 mA Current, input range: 0...20 mA Voltage, input range: 0...10 V
Analogue input resolution	16 bits
LSB value	1 mV (voltage), output range: 0...10 V 2 $\mu$ A (current), output range: 0...20 mA 2 $\mu$ A (current), output range: 4...20 mA
Sampling duration	10 ms
Absolute accuracy error	+/- 0.2 % of full scale 25 °C
Temperature drift	+/- 0.006 %FS/°C
Repeat accuracy	+/- 0.2 %FS
Non-linearity	+/- 0.05 %FS
Cross talk	80 dB
Type of cable	Twisted shielded pairs cable
Electrical connection	1 spring terminal block (pitch 3.81 mm) 1.5 mm <sup>2</sup> 1 for inputs and supply
Cable distance between devices	Twisted shielded pairs cable: 30 m for input
Insulation	Non-insulated between inputs Between input and internal logic 500 V DC
Supply voltage limits	20.4...28.8 V
Local signalling	1 LED green PWR
Height	50 mm
Depth	21 mm
Width	34 mm
Product weight	0.055 kg
Permissible continuous overload	40 mA (current) 30 V (voltage)
Input impedance	>= 1 MOhm voltage <= 250 Ohm current

### Okolina

immunity to microbreaks	10 ms
-------------------------	-------

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1350 - Schneider Electric declaration of conformity	Compliant - since 1350 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

---

Available

Available

---

Available

Available

---