



### Glavno

Range	Prisma
Range compatibility	Prisma G
Product or component type	Mounting plate
Accessory / separate part category	Installation accessory
Installed device	Fupact: fixed ISFT160 - control: fuse carriers handle - vertical installation Fupact: fixed ISFT100N - control: fuse carriers handle - vertical installation
Poles description	4 x 3P: fixed: ISFT160 vertical installation 6 x 3P: fixed: ISFT100N vertical installation

### Komplementarno

Enclosure/cubicle description	Floor-standing enclosure - width 600 mm Wall-mounted enclosure - width 600 mm
Number of vertical modules [50 mm]	8 module(s) : ISFT100N, rear connection on busbar in 600 mm Wide floor-standing enclosure 8 module(s) : ISFT100N, rear connection on busbar in 600 mm Wide wall-mounted enclosure 8 module(s) : ISFT160, rear connection on busbar in 600 mm Wide floor-standing enclosure 8 module(s) : ISFT160, rear connection on busbar in 600 mm Wide wall-mounted enclosure
Height	250 mm
Product weight	4.26 kg
Colour	White RAL 9001

### Okolina

standards	IEC 61439-2
product certifications	ASEFA

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0815 - Schneider Electric declaration of conformity	Compliant - since 0815 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations

### Contractual warranty

Warranty period	18 months
-----------------	-----------

Informacije dane u ovoj dokumentaciji sadrže opće i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih podružnica nećete preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.