



Glavno

| | |
|------------------------------------|--|
| Range | Prisma |
| Range compatibility | Prisma G |
| Product or component type | Front plate |
| Accessory / separate part category | Installation accessory |
| Type of front plate | Cut-out |
| Installed device | Power meters: kilowatt-hour meters - vertical installation |
| Poles description | 2 x 4P: mounting plate support: kilowatt-hour meters vertical installation |

Komplementarno

| | |
|------------------------------------|--|
| Enclosure/cubicle description | Floor-standing enclosure - width 600 mm Wall-mounted enclosure - width 600 mm |
| Type of front cover | Metering |
| Number of vertical modules [50 mm] | 9 |
| Standards | IEC 61439-2 IEC 61439-1 |
| Product certifications | ASEFA |
| Quantity per set | Set of 1 |
| Height | 450 mm |
| Width | 500 mm |
| Product weight | 3.82 kg |
| Material | Steel |
| Surface finish | Matt Smooth |
| Protective treatment | Electrophoresis treatment and hot-polymerised polyester epoxy powder |
| Colour | White RAL 9001 |

Okolina

| | |
|-------------------------|---------------------------------|
| IK degree of protection | IK07 conforming to EN/IEC 62262 |
|-------------------------|---------------------------------|

Offer Sustainability

| | |
|---|---|
| Green Premium product | Green Premium product |
| Compliant - since 0807 - Schneider Electric declaration of conformity | Compliant - since 0807 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Need no specific recycling operations | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.