

## GV3B22

TeSys GV3 – podnaponski otpusnik – 220 V AC 50 Hz



### Glavno

Range	TeSys
Device short name	GV3B
Product or component type	Undervoltage trip
Device application	Control

### Komplementarno

Product compatibility	GV3ME
[Uc] control circuit voltage	220 V AC 50 Hz 240 V AC 50 Hz 277 V AC 60 Hz
Control circuit voltage limits	0.8...1.1 Un
[Ui] rated insulation voltage	600 V AC UL 508 690 V AC IEC 60947-1 600 V AC CSA C22.2 No 14
Threshold tripping voltage	0.7...0.35 Un
Inrush power in VA	12 VA AC
Inrush power in W	7 W DC
Hold-in power consumption in VA	7 VA AC
Hold-in power consumption in W	2.5 W DC
Operating time	10 ms IEC 60947-1
On-load factor	100 %
Connections - terminals	Screw clamp terminals 1 0.75...2.5 mm <sup>2</sup> flexible without Screw clamp terminals 1 1...2.5 mm <sup>2</sup> solid Screw clamp terminals 2 0.75...2.5 mm <sup>2</sup> flexible without Screw clamp terminals 2 1...2.5 mm <sup>2</sup> solid Screw clamp terminals 1 0.75...2.5 mm <sup>2</sup> flexible with Screw clamp terminals 2 0.75...2.5 mm <sup>2</sup> flexible with
Tightening torque	1.2 N.m screw clamp terminals
Mechanical durability	15000 cycles
Quantity per set	Set of 10
Product weight	0.07 kg

### Okolina

#### Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0723 - Schneider Electric declaration of conformity	Compliant - since 0723 - Schneider Electric declaration of conformity
Reference contains SVHC above the threshold - go to CaP for more details	Reference contains SVHC above the threshold

#### Contractual warranty

Warranty period	18 months
-----------------	-----------

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.