

## KBC16DCF22

Canalis – razvodna jedinica za NF osigurače – 8,5 x 31,5 – 16 A – odabir faze



### Glavno

Range	Canalis
Product or component type	Tap-off unit
Product compatibility	KBA KBB KDP
Device application	Lighting
Range compatibility	Canalis KBA Canalis KBB Canalis KDP

### Komplementarno

[Ue] rated operational voltage	230...400 V
[Ui] rated insulation voltage	690 V
[Ie] rated operational current	16 A at 35 °C
Network frequency	50/60 Hz
Busbar trunking polarity	L2 + L1 + L3 + PE
Protection type	Fuse
Fuse type	Cylindrical : 8.5 x 31.5 mm - gG conforming to NF
Tap-off lock colour	Yellow
Tap-off unit polarity	L1+L2 L1+L3 L2+L3
Tap-off unit connector type	With phase selection
Provided equipment	Fuse not supplied
Standards	EN/IEC 60439-2 EN/IEC 61439-6
Width	168 mm
Depth	33 mm
Height	53 mm
Colour	RAL 9001 : cream
Product weight	90 g
Quantity per set	Set of 10

### Okolina

IP degree of protection	IP55 conforming to EN/IEC 60529
-------------------------	---------------------------------

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1010 - Schneider Electric declaration of conformity	Compliant - since 1010 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations

### Contractual warranty

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

