

VW3A9544

komplet kućišta s podnim stankom IP54–za pogon
promjenjive brzine–ATV61/ATV71



Glavno

| | |
|---------------------------------------|---|
| Accessory / separate part category | Installation accessories |
| Accessory / separate part type | Enclosure |
| Accessory / separate part designation | Pre-equipped IP54 floor-standing enclosure kit |
| Product compatibility | ATV61HC22N4 ATV71HC16N4 |
| Accessory / separate part destination | Create an IP54 floor-standing enclosure for variable speed drives |
| Range compatibility | Altivar 61 Altivar 71 |

Komplementarno

| | |
|-----------------|--|
| Kit composition | 24 V DC, 600 mA supplementary power supply Air/air heat exchanger Altivar 61 and 61 identification labels Document holder Drive support EMC plate Fixing accessories Handle with a push-button operated opening mechanism IP65 graphic display terminal remote mounting kit Lower air duct Plinth Roof extension Seals Upper air duct |
| Colour code | RAL 7022 plinth RAL 7032 case |
| Cable entry | Via the enclosure bottom or from the left |
| Supply | 1 internal additional supply 24 V DC <= 600 mA 1 internal drive supply 24 V DC 21...27 V <= 200 mA |
| Product weight | 252 kg |

Okolina

| | |
|---------------------------------------|---|
| ambient air temperature for operation | 0...45 °C outside the enclosure 0...50 °C inside the enclosure |
|---------------------------------------|---|

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.
Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.
Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poipunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.
Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.